



## 4801 Weather Radio Pre-Amp/Pre-Selector

Ever wished for just a little more signal from your local National Weather Radio station? Tired of interfering signals? MTS has the solution! The 4801 NOAA Pre-Amp offers 16 dB of gain with a band pass filter Q greater than 200! The 4801 offers over 30 dB of attenuation to paging transmitters at 158.7 MHz.

### Specifications

Size:	1.6 (W) x 2.0 (D) x 1.0(H)
Input Power:	9 Vdc @ 100 mA
Input Impedance:	50 ohms
Output Impedance:	50 ohms
RF Input Connector Type:	BNC
RF Output Connector Type:	BNC
Center Frequency:	162.475 MHz
Nominal Gain:	16 dB
-3dB (from maximum gain):	+/- 75 kHz from center frequency
Noise Figure:	1dB

Suggested Retail Price: \$69.95  
Order MTS Part Number: 4801-000

Multi-Technical Services, Inc.  
150 Clayton Commerce Center  
Clayton, NC 27520  
919-553-2995 Phone  
919-553-0437 Fax

[www.mts-comm.com](http://www.mts-comm.com)